



PL20, PL40, PL60 Energy System Controllers



12, 24, 32, 36 and 48V in one controller

Built-in 30 days datalogger

Multifunctional 3 digit LC Display

External current sensing (optional)

RS232 interface (optional)

Hybrid system control

Widely programmable

Built-in programmable logic



The PL series of charge controllers offer complete control over the charge cycle and various information about current and past performance.

PL regulators have a built-in low battery disconnect switch. In addition, the versatile event controller can switch power on or off according to criteria set by the user. This allows the PL to do extra tasks such as switching a light on at night or keeping a water tank full by operating a pump when needed.

Regulation can be done in both series and shunt modes. Other features include backup generator control and charging a second battery.

Display shows battery voltage, charge current, ampere hours in and out of battery, load being drawn from the battery and charge status.

Information is available for the past 30 days - so even if the user doesn't remember what happened, the regulator will.

With the optional PLI interface, the user can access the regulator from a computer or via modem. Data can be read or settings adjusted.

PL

Phocos AG, Germany
info@phocos.com

Phocos Europe GmbH, Austria
info-europe@phocos.com

Phocos Eastern Europe S.R.L., Romania
info-easterneurope@phocos.com

Phocos China Ltd., China
info-china@phocos.com

Phocos India Solar Pvt. Ltd., India
info-india@phocos.com

Phocos SEA Pte Ltd, Singapore
info-sea@phocos.com

Phocos Latin America S.R.L, Bolivia
info-latinamerica@phocos.com

Phocos Rep. Office Brazil, Brazil
info-brazil@phocos.com

Phocos Rep. Office Eastern Africa, Kenya
info-easternfrica@phocos.com

Phocos Rep. Office Southern Africa, Namibia
info-sadc@phocos.com

Phocos SunDanzer, USA
info-usa@phocos.com

Phocos Rep. Office Australia, Australia
info-australia@phocos.com

| | PL 20 | PL 40 | PL 60 |
|---------------------------|----------------------------------|----------------------------------|----------------------------------|
| Nominal Voltage | 12, 24, 32, 36, 48 V | 12, 24, 32, 36, 48 V | 12, 24, 32, 36, 48 V |
| Solar Charge Current max. | 20 A | 40 A | 60 A |
| Load Current max. | 20 A | 7 A | 30 A |
| Max voltage Drop | 0,4 V | 0,4 V | 0,42 V |
| Ambient Temperature | -20 to +55 °C | -20 to +55 °C | -20 to +55 °C |
| Supply Current | 9 mA | 13 mA | 20 mA |
| Temperature Sensor Range | -15 to +50 °C | -15 to +50 °C | -15 to +50 °C |
| Regulation Set Points | 4 preset programs, 1 user adjust | 4 preset programs, 1 user adjust | 4 preset programs, 1 user adjust |
| Dimensions (h x w x d) | 100 x 109 x 41 | 130 x 124 x 50 | 225 x 175 x 62 |